



100 Amp Service Pole:
 #2 or #4 wire, #4 neutral
 #4 service ground
 All wire shall be copper.

200 Amp Service Pole:
 #2/0 wire, #1 neutral
 #4 service ground
 All wire shall be copper.

NOTES:

Pole may be a round treated pole or 6" x 6" lumber, 16' in length, 4' in ground
 Service wires must be no less than 12' from ground.

The service wires must be 16' if over a driveway,

****Article 210-7 (NATIONAL ELECTRIC CODE)**

All receptacle outlets on single - phase circuits
 for construction sites shall have approved ground - fault protection.
 Bolivar Energy Authority Engineers must spot location
 of construction meter pole before any wiring.



BOLIVAR ENERGY AUTHORITY

**TEMPORARY SERVICE
 POLE REQUIREMENT**

DATE: 03-2008

TSP-BEA